

# GSM Door Phone SMS Control

Command format: <password>#<command type>#<data1>[\_,<data2>,<data3>,<data...>]#

Description	Command	SMS Response	Remarks	Example
01 Default Password	<password>#01#123456#	Reset to Default Password 123456	default=123456	123456#01#123456#
02 Change Password	<password>#02#<new password>#	New Password <new password>	00000~999999	123456#02#266922#
03 Set Manager Phone Number	<password>#03#< manager phone number>#	Manager Phone Number <manager phone number>	20 digits maximum	123456#03#037266922#
04 Get Manager Phone Number	<password>#04#	Manager Phone Number <manager phone number>	20 digits maximum	123456#04#
05 Set Microphone Volume	<password>#05#<microphone volume>#	Microphone Volume <microphone volume>	<microphone volume>=1~9	123456#05#4#
06 Get Microphone Volume	<password>#06#	Microphone Volume <microphone volume>	<microphone volume>=1~9	123456#06#
07 Set Speaker Volume	<password>#07#<speaker volume>#	Speaker Volume <speaker volume>	<speaker volume>=1~9	123456#07#4#
08 Get Speaker Volume	<password>#08#	Speaker Volume <speaker volume>	<speaker volume>=1~9	123456#08#
09 Set Talking Time	<password>#09#<time>#	Talking Time <time>	<time>1~99min	123456#09#3#
10 Get Talking Time	<password>#10#<time>#	Talking Time <time>	<time>=1~99min	123456#10#
11 Get Firmware Version	<password>#11#	Firmware Version <version>		123456#11#
12 Set Open Door by Password	<password>#12#<function>#<open door password>#	Open Door by Password is Enabled(Disabled)<open door password>	<function> =1(enable); =0(disable) <open door password>= 00000~999999	123456#12#1#266922#
13 Set Door Open Time	<password>#13#<dooropen time>#	Door Open Time <door open time>	<door open time>=2~99s	123456#13#3#
14 Set Door Relay Type	<password>#14#<door relay type>#	Door Relay Type is Normal Open(or Close)	<door relay type>: 0=normal open 1=normal close	123456#14#1#

Description	Command	SMS Response	Remarks	Example
15 Set Calling Time	<password>#15#<calling time>#	Calling Time <calling time>	<calling time>=25~99s	123456#15#30#
16 Set Calling by List	<password>#16#<function>#	Calling List is Enabled( or Disabled)	<function>: 0=disable 1=enable	123456#16#1#
17 Set Incoming Call	<password>#17#<auto answer>#<wait rings>#<ringer>#	Auto Answer is ON(or OFF) Wait for <wait rings> Rings Ringer is ON(OFF)	<auto answer>: 0=OFF 1=ON <wait rings>: 1~9 <ringer>: 0=OFF 1=ON	123456#17#1#3#0# 123456#17#0#3#1#
18 Set Greetings	<password>#18#<greeting option >[, <line1>, <line2>, <line3>]#	Greetings: Enter Flat Number then Call (or Welcome!)(or line1__line2__line3)	<greeting option>: 1=Enter Flat Number then Call 2=Welcome! 3=user defined <line1>: 16 char <line2>: 16 char <line3>: 16 char	123456#18#1# 123456#18#2# (use line1,line2,line3) 123456#18#3, Press, CALL, for Assistant# (use line1) 123456#18#3, Press CALL key,.#
19				
20 Add Subscriber	<password>#20#<id>, <name>, <phone1>[, <phone2>], <inhibit>#	Subscriber Added, <id>, <name>, <phone1>[, <phone2>], Normal( or Inhibit) or Subscriber NOT Added, <id> - Memory Full! or Subscriber NOT Added, <id> - ID existed!	[<phone2>] is optional 1-phone number model: 16 digits maximum 2-phone number model: 20 digits maximum	1-phone number: 123456#20#1, Peter,037266 922, 0# 2-phone number: 123456#20#1, Peter,037266 922, 037266923, 0#

Description	Command	SMS Response	Remarks	Example
21 Change Subscriber	<password>#21#<id>,<name>,<phone1>[,<phone2>],<inhibit>#	Subscriber Changed, <id>,<name>,<phone1>[,<phone2>],Normal( or Inhibit)  Subscriber NOT Changed,<id> – ID is not existed!	[<phone2>] is optional 1-phone number model: 16 digits maximum 2-phone number model: 20 digits maximum	1-phone number: 123456#20#1,Peter,037266 922,0#  2-phone number: 123456#20#1,Peter,037266 922,037266923,0#
22 Delete Subscriber	<password>#22#<id>#	Subscriber Deleted, <id>,<name>,<phone1>[,<phone2>],Normal( or Inhibit)  Subscriber NOT Deleted,<id> – ID is not existed!		123456#22#1#
23 Inquire Subscriber	<password>#23#<id>#	Subscriber Inquired, <id>,<name>,<phone1>[,<phone2>],Normal( or Inhibit)  Subscriber Inquired,<id> – ID is not existed!		123456#23#1#

SMS responses messages of GSM Door phone:

- Wrong Data Format
- Wrong Command
- Wrong Password
- Invalid Password
- Invalid Phone Number
- Unknown Message