

MH 2000, personlig tracker

MH2000 er en NY GPS sender. Har en stor knapp for å utløse alarm. Sender SMS med koordinater. Kun sporing, ikke samtale. Mål: 92 x 44 x 18 mm,

MH2000 er en enkel programmerbar "smart tracking" enhet som kombinerer GPS og GSM teknologi. Enheten er fullt tilpasset brukerens behov. Dens hovedområde er å fungere som en mobil sporings enhet for forskjellige sikkerhets systemer og programmer.

Nøkkelfunksjoner:

Enkel å bruke og konfigurere, lett tilgjengelig alarm knapp, lang batteri levetid, 65 kanals GPS mottaker, Dual band GSM modul, SMS forespørsler, tilbakemeldinger, fjernstyrings instillinger, internett sporing/ 24 coordinates history Personlig sikkerhet, advarsler om utladet batteri

MH2000 Generelle spesifikasjoner:

*GPS receiver - YES (-161dBm / 65 channels),
Internal GPS antenna - Patch (Dimensions: 25 x 25 x 4), GSM module - YES, Frequencies (MHz) - 900/1800 or 850/1900 Keyboard - 2 (Alarm and turn on/off buttons), Battery - 1050 mAh (Li-ion) LED indicators - Battery / GSM / GPS-Alarm, Weight - 80g (with battery)
Data transfer, SMS - Requests / Alarm, Connection to a PC Connector - YES (Firmware update and debug) Configuration, Configuration via SMS - YES*

Internal memory - 24 coordinates, Recommended operating temperature 0 up to 50°C Storage temperature - -20 up to 60°C Battery life 24 coord./day - 150 hour. Battery life 24 1 coord./day - 350 hour, Battery life sleep - 420 hour

